



### 1 产品概述 Product Summarize

用于发电机、变压器和输电线的过负荷和短路保护线路中，作为启动元件。电磁式瞬动型。

It's used in protection lines against over-load and short circuit for generator, transformer and transmitting lines, working as starter.

Electromagnetic instantaneous action type.

### 2 主要技术参数 Main Technological Parameter

型号 type	DL-21C	DL-22C	DL-23C	DL-24C	DL-25C
触点形式 Contact form	1 副动合 1 pair of movable connection	1 副动断 1 pair of movable disconnection	1 副动合, 1 副动断 1 pair of movable-connection and movable-disconnection	2 副动合 2 pairs of movable-connections	2 副动断 2 pairs of movable-disconnections
最大整定电流(A) Max. setting current (A)	0.05, 0.2, 0.6, 2, 6, 10, 20, 50, 100, 200				
返回系数 Return coefficient	最大整定电流 200A 的返回系数不低于 0.7, 其余规格不低于 0.8 Return coefficient not less than 0,7 as max. setting current of 200A, others, not less than 0,8				
动作时间(s) Action time (s)	1.2 倍整定值时 $\leq 0.15$ , 3 倍整定值时 $\leq 0.03$ 1.2 times of setting value, $\leq 0,15$ , 3 times of setting value, $\leq 0,03$				
触点断开容量 Breaking capacity of contact	直流有感电路为 40W, 交流电路为 200VA DC sensitive circuit, 40W, AC circuit, 200VA.				

### 3 安装开孔尺寸、接线图 Mounging plate opening size, Wiring drawing

