



1 产品概述 Product Summarize

JDZ1 系列组合式中间继电器是一种多功能的空气电磁式继电器。本系列继电器包括有中间继电器锁扣继电器。继电器适用于交流，电压 380 伏及以下，直流电压制 220 伏及以下的控制电路中，主要用以控制各种电磁线圈接触器具有吸引线圈断电“记忆”功能，可作为自动控制系统“记忆”元件。

JDZ1 series compound middle relays are multifunctional air electromagnetic relays. This series include middle relay and lock relay. This series can be used in controlling circuit of AC and voltage $\leq 380V$, or DC and voltage $\leq 220V$. This series are applying for controlling all kinds of electromagnetic coil contactors, and have the function of attracting coil power-off "memory", and can be used as "memory" elements of automatic controlling system.

2 主要技术参数 Main Technological Parameter

型号 Type	JDZ1-22	JDZ1-40	JDZ1-44	JDZ1-62	JDZ1-80	JDZ1-12K	JDZ1-30K	JDZ1-52K
电压种类 Voltage type	交流，直流 AC, DC							
接点电压(V) Contact voltage	AC 交流: 24,48,110,220,380; 直流: 24,48,110,220 DC							
接点额定电流(A) Contact rated current (A)	5							
额定操作频率(次/小时) Rated operating Frequency (times/hour)	中间继电器 1200, 锁扣继电器 600 Middle relay 1200, lock relay 600							
接点组合 Contact combination	2 常开 2 常闭 2 normally open, 2 normally closed	4 常开 4 normally open	4 常开 4 常闭 4 normally open, 4 normally closed	6 常开 2 常闭 6 normally open, 2 normally closed	8 常开 28 常开 8 normally open	1 常开 2 常闭 1 normally open, 2 normally closed	3 常开 3 normally open	5 常开 2 常闭 5 normally open, 2 normally closed

3 安装开孔尺寸、接线图 Mounging plate opening size, Wiring drawing

