



1 产品概述 Product Summarize

DZ-30B系列中间继电器用于直流操作的各种保护和自动控制线路中，作为辅助继电器以增加触点数量和触点容量。

继电器为电磁式动作继电器。

DZ-30B series Middle-relays are applying for all kinds of protective and automatic control circuit operated by DC. It works as auxiliary relay to increase contact number and contact capacity.

This series are electromagnetic operating relays.

2 主要技术参数 Main Technological Parameter

型号 Type	DZ-31B	DZ-32B
触点形式 Contact type	3副动合,3副转换 3 pairs of move to match, 3pair of switching	6副动合 6 pairs of move to match
额定电压(V) Rated voltage	220,110,48,24,12	
动作电压(V) Operation voltage	不大于 70%Un	≤70%Un
返回电压(V) Return voltage	不小于 5%Un	≥5%Un
动作时间(ms) Operating time	Under rated voltage, 额定电压下 ≤ 45	
触点断开容量 Contact breaking capacity	直流有感负荷 50W 交流电路 250VA DC inductive load 50W, AC circuit 250VA	

3 安装开孔尺寸、接线图 Mounging plate opening size,Wiring drawing

